

Fortinet

Exam Questions NSE7_SDW-7.0

Fortinet NSE 7 - SD-WAN 7.0



NEW QUESTION 1

Refer to the exhibits.

Exhibit A

```
config duplication
edit 1
    set srcaddr "10.0.1.0/24"
    set dstaddr "10.1.0.0/24"
    set srcintf "port5"
    set dstintf "overlay"
    set service "ALL"
    set packet-duplication force
next
end

branch1_fgt # diagnose sys sdwan zone
Zone SASE index=2
    members(0):
Zone overlay index=4
    members(3): 19(T_INET_0_0) 20(T_INET_1_0) 21(T_MPLS_0)
Zone underlay index=3
    members(2): 3(port1) 4(port2)
Zone virtual-wan-link index=1
    members(0):

1.274665 port5 in 10.0.1.101 -> 10.1.0.7: icmp: echo request
1.275788 T_INET_0_0 out 10.0.1.101 -> 10.1.0.7: icmp: echo request
1.275790 T_INET_1_0 out 10.0.1.101 -> 10.1.0.7: icmp: echo request
1.275801 T_MPLS_0 out 10.0.1.101 -> 10.1.0.7: icmp: echo request
1.278365 T_INET_1_0 in 10.1.0.7 -> 10.0.1.101: icmp: echo reply
1.278553 port5 out 10.1.0.7 -> 10.0.1.101: icmp: echo reply
```

Exhibit B

```
3.874431 T_INET_1_0 in 10.0.1.101 -> 10.1.0.7: icmp: echo request
3.874630 port5 out 10.0.1.101 -> 10.1.0.7: icmp: echo request
3.874895 T_INET_0_0 in 10.0.1.101 -> 10.1.0.7: icmp: echo request
3.875125 T_MPLS_0 in 10.0.1.101 -> 10.1.0.7: icmp: echo request
3.875054 port5 in 10.1.0.7 -> 10.0.1.101: icmp: echo reply
3.875308 T_INET_1_0 out 10.1.0.7 -> 10.0.1.101: icmp: echo reply
```

Exhibit A shows the packet duplication rule configuration, the SD-WAN zone status output, and the sniffer output on FortiGate acting as the sender. Exhibit B shows the sniffer output on a FortiGate acting as the receiver.

The administrator configured packet duplication on both FortiGate devices. The sniffer output on the sender FortiGate shows that FortiGate forwards an ICMP echo request packet over three overlays, but it only receives one reply packet through T_INET_1_0.

Based on the output shown in the exhibits, which two reasons can cause the observed behavior? (Choose two.)

- A. On the receiver FortiGate, packet-de-duplication is enabled.
- B. The ICMP echo request packets sent over T_INET_0_0 and T_MPLS_0 were dropped along the way.
- C. The ICMP echo request packets received over T_INET_0_0 and T_MPLS_0 were offloaded to NPU.
- D. On the sender FortiGate, duplication-max-num is set to 3.

Answer: AD

NEW QUESTION 2

Which diagnostic command can you use to show the member utilization statistics measured by performance SLAs for the last 10 minutes?

- A. diagnose sys sdwan intf-sla-log
- B. diagnose sys sdwan health-check
- C. diagnose sys sdwan log
- D. diagnose sys sdwan sla-log

Answer: D

Explanation:

SD-WAN 7.2 Study Guide page 321 You can view the stored member metrics by running the diagnose sys sdwan sla-log command. Note that you must include the name of the performance SLA followed by the member configuration index number. To display the SLA logs per interface, you run the diagnose sys sdwan intf-sla-log command.

NEW QUESTION 3

What are two reasons for using FortiManager to organize and manage the network for a group of FortiGate devices? (Choose two)

- A. It simplifies the deployment and administration of SD-WAN on managed FortiGate devices.
- B. It improves SD-WAN performance on the managed FortiGate devices.
- C. It sends probe signals as health checks to the beacon servers on behalf of FortiGate.
- D. It acts as a policy compliance entity to review all managed FortiGate devices.

E. It reduces WAN usage on FortiGate devices by acting as a local FortiGuard server.

Answer: AE

NEW QUESTION 4

Which are three key routing principles in SD-WAN? (Choose three.)

- A. FortiGate performs route lookups for new sessions only.
- B. Regular policy routes have precedence over SD-WAN rules.
- C. SD-WAN rules have precedence over ISDB routes.
- D. By default, SD-WAN members are skipped if they do not have a valid route to the destination.
- E. By default, SD-WAN rules are skipped if the best route to the destination is not an SD-WAN member.

Answer: BDE

NEW QUESTION 5

What are two reasons why FortiGate would be unable to complete the zero-touch provisioning process? (Choose two.)

- A. The FortiGate cloud key has not been added to the FortiGate cloud portal.
- B. FortiDeploy has connected with FortiGate and provided the initial configuration to contact FortiManager
- C. The zero-touch provisioning process has completed internally, behind FortiGate.
- D. FortiGate has obtained a configuration from the platform template in FortiGate cloud.
- E. A factory reset performed on FortiGate.

Answer: AC

NEW QUESTION 6

Refer to the exhibit.

```
branch1_fgt # diagnose firewall proute list
list route policy info(vf=root):

id=1 dscp_tag=0xff 0xff flags=0x0 tos=0x00 tos_mask=0x00 protocol=17 sport=0-65535 iif=7
dport=53 path(1) oif=3(port1)
source wildcard(1): 0.0.0.0/0.0.0.0
destination wildcard(1): 4.2.2.1/255.255.255.255
hit_count=0 last_used=2022-03-25 10:53:26

id=2131165185(0x7f070001) vwl_service=1(Critical-DIA) vwl_mbr_seq=1 2 dscp_tag=0xff 0xff
flags=0x0 tos=0x00 tos_mask=0x00 protocol=0 sport=0-65535 iif=0 dport=1-65535 path(2)
oif=3(port1) oif=4(port2)
source(1): 10.0.1.0-10.0.1.255
destination wildcard(1): 0.0.0.0/0.0.0.0
internet service(3): GoToMeeting(4294836966,0,0,0, 16354)
Microsoft.Office.365.Portal(4294837474,0,0,0, 41468) Salesforce(4294837976,0,0,0, 16920)
hit_count=0 last_used=2022-03-24 12:18:16

id=2131165186(0x7f070002) vwl_service=2(Non-Critical-DIA) vwl_mbr_seq=2 dscp_tag=0xff
0xff flags=0x0 tos=0x00 tos_mask=0x00 protocol=0 sport=0-65535 iif=0 dport=1-65535
path(1) oif=4(port2)
source(1): 10.0.1.0-10.0.1.255
destination wildcard(1): 0.0.0.0/0.0.0.0
internet service(2): Facebook(4294836806,0,0,0, 15832) Twitter(4294838278,0,0,0, 16001)
hit_count=0 last_used=2022-03-24 12:18:16

id=2131165187(0x7f070003) vwl_service=3(all_rules) vwl_mbr_seq=1 dscp_tag=0xff 0xff
flags=0x0 tos=0x00 tos_mask=0x00 protocol=0 sport=0-65535 iif=0 dport=1-65535 path(1)
oif=3(port1)
source(1): 0.0.0.0-255.255.255.255
destination(1): 0.0.0.0-255.255.255.255
hit_count=0 last_used=2022-03-25 10:58:12
```

Based on the output, which two conclusions are true? (Choose two.)

- A. There is more than one SD-WAN rule configured.
- B. The SD-WAN rules take precedence over regular policy routes.
- C. The all_rules rule represents the implicit SD-WAN rule.
- D. Entry 1(id=1) is a regular policy route.

Answer: AD

NEW QUESTION 7

Refer to the exhibit.

Create New SD-WAN Interface Member

Sequence Number	<input type="text" value="1"/>
Interface Member	<input type="text"/>
SD-WAN Zone	<div style="border: 1px solid #ccc; padding: 2px; display: flex; align-items: center;"> virtual-wan-link ▼ </div>
Gateway IP	<input type="text" value="0.0.0.0"/>
Cost	<input type="text" value="0"/>
Status	<div style="display: flex; align-items: center;"> <input checked="" type="checkbox"/> </div>
Priority	<input type="text" value="0"/>
Advanced Options >	

Which two SD-WAN template member settings support the use of FortiManager meta fields? (Choose two.)

- A. Cost
- B. Interface member
- C. Priority
- D. Gateway IP

Answer: BD

NEW QUESTION 8

Which two conclusions for traffic that matches the traffic shaper are true? (Choose two.)

```
# diagnose firewall shaper traffic-shaper list name VoIP_Shaper
name VoIP_Shaper
maximum-bandwidth 6250 KB/sec
guaranteed-bandwidth 2500 KB/sec
current-bandwidth 93 KB/sec
priority 2
overhead 0
tos ff
packets dropped 0
bytes dropped 0
```

- A. The traffic shaper drops packets if the bandwidth is less than 2500 KBps.
- B. The measured bandwidth is less than 100 KBps.
- C. The traffic shaper drops packets if the bandwidth exceeds 6250 KBps.
- D. The traffic shaper limits the bandwidth of each source IP to a maximum of 6250 KBps.

Answer: BC

NEW QUESTION 9

Which two protocols in the IPsec suite are most used for authentication and encryption? (Choose two.)

- A. Encapsulating Security Payload (ESP)
- B. Secure Shell (SSH)
- C. Internet Key Exchange (IKE)
- D. Security Association (SA)

Answer: AC

NEW QUESTION 10

Which statement is correct about SD-WAN and ADVPN?

- A. Routes for ADVPN shortcuts must be manually configured.
- B. SD-WAN can steer traffic to ADVPN shortcuts, established over IPsec overlays, configured as SD-WAN members.
- C. SD-WAN does not monitor the health and performance of ADVPN shortcuts.
- D. You must use IKEv2 on IPsec tunnels.

Answer: B

NEW QUESTION 10

Refer to the exhibit.


```
config system settings
  set firewall-session-dirty check-new
end
```

Based on the exhibit, which two actions does FortiGate perform on sessions after a firewall policy change? (Choose two.)

- A. FortiGate flushes all sessions.
- B. FortiGate terminates the old sessions.
- C. FortiGate does not change existing sessions.
- D. FortiGate evaluates new sessions.

Answer: CD

Explanation:

FortiGate not to flag existing impacted session as dirty by setting firewall-session-dirty to check new. The results is that FortiGate evaluates only new session against the new firewall policy.

NEW QUESTION 14

What are two benefits of using forward error correction (FEC) in IPsec VPNs? (Choose two.)

- A. FEC supports hardware offloading.
- B. FEC improves reliability of noisy links.
- C. FEC transmits parity packets that can be used to reconstruct packet loss.
- D. FEC can leverage multiple IPsec tunnels for parity packets transmission.

Answer: BC

NEW QUESTION 18

What are two benefits of using the Internet service database (ISDB) in an SD-WAN rule? (Choose two.)

- A. The ISDB is dynamically updated and reduces administrative overhead.
- B. The ISDB requires application control to maintain signatures and perform load balancing.
- C. The ISDB applies rules to traffic from specific sources, based on application type.
- D. The ISDB contains the IP addresses and port ranges of well-known internet services.

Answer: AD

NEW QUESTION 19

Which two statements about SD-WAN central management are true? (Choose two.)

- A. The objects are saved in the ADOM common object database.
- B. It does not support meta fields.
- C. It uses templates to configure SD-WAN on managed devices.
- D. It supports normalized interfaces for SD-WAN member configuration.

Answer: AC

Explanation:

Normalized interfaces are not supported for SD-WAN templates. You can create multiple SD-WAN zones and add interface members to the SD-WAN zones. You must bind the interface members by name to physical interfaces or VPN interfaces.<https://docs.fortinet.com/document/fortigate/7.0.0/sd-wan-new-features/794804/new-sd-wan-template>

NEW QUESTION 22

Refer to the exhibit.

```
branch1_fgt # diagnose sys sdwan service 1

Service(3): Address Mode(IPV4) flags=0x200 use-shortcut-sla
Gen(6), TOS(0x0/0x0), Protocol(0: 1->65535), Mode(manual)
Members(2):
  1: Seq_num(3 T_INET_0_0), alive, selected
  2: Seq_num(4 T_INET_1_0), alive, selected
Src address(1):
  10.0.1.0-10.0.1.255

Dst address(1):
  10.0.0.0-10.255.255.255

branch1_fgt # diagnose sys sdwan member | grep T_INET_
Member(3): interface: T_INET_0_0, flags=0x4 , gateway: 100.64.1.1, priority: 10 1024,
weight: 0
Member(4): interface: T_INET_1_0, flags=0x4 , gateway: 100.64.1.9, priority: 0 1024,
weight: 0

branch1_fgt # get router info routing-table all | grep T_INET_
S      10.0.0.0/8 [1/0] via T_INET_1_0 tunnel 100.64.1.9
```

An administrator is troubleshooting SD-WAN on FortiGate. A device behind branch1_fgt generates traffic to the 10.0.0.0/8 network. The administrator expects the traffic to match SD-WAN rule ID 1 and be routed over T_INET_0_0. However, the traffic is routed over T_INET_1_0. Based on the output shown in the exhibit, which two reasons can cause the observed behavior? (Choose two.)

- A. The traffic matches a regular policy route configured with T_INET_1_0 as the outgoing device.
- B. T_INET_1_0 has a lower route priority value (higher priority) than T_INET_0_0.
- C. T_INET_0_0 does not have a valid route to the destination.
- D. T_INET_1_0 has a higher member configuration priority than T_INET_0_0.

Answer: AC

Explanation:

<https://community.fortinet.com/t5/FortiGate/Technical-Tip-Assigning-Priority-to-SD-WAN-Members-for-Defau>

NEW QUESTION 26

Refer to the exhibit.

```
# get router info routing-table all
...
B      10.0.2.0/24 [200/0] via 10.201.1.2 [3] (recursive via VPN0 tunnel 100.64.1.1), 00:00:54
          [200/0] via 10.202.1.2 [3] (recursive via VPN1 tunnel 100.64.1.9), 00:00:54
          [200/0] via 10.203.1.1 [3] (recursive via VPN2 tunnel 172.16.1.5), 00:00:54
...
```

The device exchanges routes using IBGP.

Which two statements are correct about the IBGP configuration and routing information on the device? (Choose two.)

- A. Each BGP route is three hops away from the destination.
- B. ibgp-multipath is disabled.
- C. additional-path is enabled.
- D. You can run the get router info routing-table database command to display the additional paths.

Answer: CD

NEW QUESTION 28

.....

Thank You for Trying Our Product

We offer two products:

1st - We have Practice Tests Software with Actual Exam Questions

2nd - Questions and Answers in PDF Format

NSE7_SDW-7.0 Practice Exam Features:

- * NSE7_SDW-7.0 Questions and Answers Updated Frequently
- * NSE7_SDW-7.0 Practice Questions Verified by Expert Senior Certified Staff
- * NSE7_SDW-7.0 Most Realistic Questions that Guarantee you a Pass on Your FirstTry
- * NSE7_SDW-7.0 Practice Test Questions in Multiple Choice Formats and Updatesfor 1 Year

100% Actual & Verified — Instant Download, Please Click
[Order The NSE7_SDW-7.0 Practice Test Here](#)